TETHERS UNLIMITED, INC. SWIFT-XTRX JETHERS JILIMITED JETHERS JILIMITED JETHERS JILIMITED JETHERS JILIMITED JETHERS JET

SOFTWARE DEFINED RADIO X-BAND TRANSCEIVER

SPECIFICATIONS

FREQUENCY RANGE

7000 - 8500 MHz

RF MODULATION

BPSK / QPSK / OQPSK / 8PSK / 16APSK

FORWARD ERROR CORRECTION

LDPC/BCH/REED SOLOMON/ CONVOLUTIONAL

BANDWIDTH

50 MHz

PEAK THROUGHPUT

> 25 Mbps

INTERFACE OPTIONS

1x Ethernet, 2x RS-422, 2x LVDS, Spacewire, 1PPS/clock

TX POWER

Up to +33 dBm, finely adjustable

ANTENNA PORTS

1 TX port SMA 1 RX port SMA

RECEIVER SENSITIVITY

- 117 dBm @ 50 ksym/s, BPSK

MAX RF INPUT

- 20 dBm

MAX RF INPUT WITHOUT DAMAGE

0 dBm

FREQUENCY ACCURACY

+/- 1.5 ppm Max

INPUT VOLTAGE

9 - 34.6 VDC

DC POWER CONSUMPTION

Standby: 4W Max Tx: 22W Max

OPERATING TEMPERATURE

-30 C to +60 °C

MASS

< 300g

DIMENSIONS

90.4 mm x 98 mm x 62 mm

ENVIRONMENTAL

Pre-qualified to NASA GEVS schock/vibe

RADIATION ENVIRONMENT

10Krad TID; Baseband Board tested to 40krad

LIFETIME

3+ years, depending upon orbit

ENCRYPTION

AES-256 up & down, FIPS140-2 Level 1 available Compatible with CryptoSWIFT-T1, KI-55, KI-103

WAVEFORM / AIR INTERFACE

CCSDS Standard

APPLICATIONS

SATCOM, SmallSats, UAVs, High Altitude Aircraft

DESCRIPTION

The SWIFT-XTRX is a X-band transceiver software defined radio that has one of the smallest size, weight and power form factors for its capabilities. With a wide array of electrical interfaces and AES encryption, the SWIFT-XTRX is ideally suited to many different applications.

